

4W & 5.4W Dimmer Compatibility 30/6/2017

Item	Brand	Type	Design Min Load	4W Bulbs		5.4W Bulbs	
				Range	Test load	Range	Test load
1	Aurora	AU-DSP400X	60W	0-100%	56W	0-100%	61.6W
2	Anytronics	DP410CB	0W	0-100%	4W	0-100%	5.4W
3	Berker	283010	20W	20-100%	56W	20-100%	61.6W
4	Berker	286710	80W	15-100%	16W	15-100%	21.6W
5	Berker R	286610	20W	5-100%	16W	5-100%	27W
6	Busch Jaeger	2247 U	40W	0-100%	16W	0-100%	27W
7	Busch Jaeger	6523-U-102	3.2W	0-100%	16W	0-100%	10.8W
8	Busch Jaeger	2250 U	80W	0-100%	76W	0-100%	67W
9	Calex	2483HC	3W	0-100%	4W	0-100%	5.4W
10	Ehmann	T39.1	10W	0-100%	16W	0-100%	21.4
11	Elko	315 GLE	20W	5-100%	8W	5-100%	5.4W
12	Futronix	P400		0-100%	12W	0-100%	16.2W
13	Gira	1182 00 / I01	80W	10-100%	8W	10-100%	5.4W
14	Gira	1184 00 / I01	80W	5-100%	8W	10-100%	50.8W
15	Gira	0307 00 / I02	20W	10-100%	8W	10-100%	10.8W
16	Hamilton	LITESTAT 40-400W	40W	10-100%	12W	10-100%	10.8W
17	Helvar	454	20W	0-100%	4W	0-100%	5.4W
18	Jung	266 GDE	60W	10-100%	44W	10-100%	45.4W
19	Jung	225 NV DE	20W	0-100%	12W	0-100%	10.8W
20	Jung R	244 EX	60W	10-100%	8W	10-100%	10.8W
21	Legrand	665.114	6.4W	5-100%	8W	10-100%	5.4W
22	Legrand	7300 48	50W	10-100%	12W	10-100%	16.2W
23	LK	MEK-S 300LR 506DA116	10W	0-100%	16W	5-100%	10.8W
24	LK (FUGA)	MEK-S 300CR 506DA117	20W	10-100%	16W	10-100%	5.4W
25	Lutron	QSGR-3PCE	20W	0-100%	8W	0-100%	5.4W
26	Mode	Trailing and Leading edge	0W	0-100%	4W	0-100%	5.4W
27	Niko	310-01301	60W	10-100%	56W	10-100%	45.4W
28	Niko R	310-01601	20W	2-100%	44W	15-100%	10.8W
29	Niko	310-01701	20W	20-100%	4W	20-100%	5.4W
30	Opus (T39.07)	852.397	10W	0-100%	12W	0-100%	5.4W
31	Peha	431 HAN LED	80W	0-100%	12W	0-100%	5.4W
32	Peha	434 OA	20W	0-100%	44W	0-100%	45.4W
33	Schneider	SBD315RC		10-100%	8W	10-100%	5.4W
34	Schneider	PDV-TE2100	20W	10-100%	4W	10-100W	5.4W
35	Schneider	IBDMIP400(MIN60W)	60W	0-100%	4W	0-100%	5.4W
36	Siemens	5TC8 284	20W	5-100%	40W	0-100%	10.8W
37	Siemens	5TC8 258	60W	10-100%	24W	10-100%	10.8W
38	Singi	China	6.4W	0-100%	16W	0-100%	5.4W
39	TMN	N8-TG CEIC	3.2W	10-100%	8W	10-100%	5.4W
40	Tradim	2481, double dimmer	20W	0-100%	20W	0-100%	5.4W
41	Tradim	2490H		15-100%	16W	0-100%	16.2W
42	Vadsbo	LD220	3.2W	0-100%	4W	0-100%	5.4W
43	Vadsbo	VD200	20W	0-100%	4W	0-100%	5.4W
44	Varilight V-Pro	JQP401W	1W	20-100%	8W	15-100%	10.8W
45	Varilight V-Pro	GJP100W	1W	10-100%	4W	10-100%	5.4W
46	Varilight V-Com	KQP101W	1W	15-100%	8W	15-100%	5.4W
47	Varilight V-Com	KQP221W	15W	0-100%	8W	0-100%	5.4W
48	Varilight V-Pro	IQP1001W	60W	20-100%	40W	20-100%	27W
49	Viribright	China	20W	0-100%	4W	0-100%	5.4W
50	Wintop (Gamma)	13212	50W	15-100%	40W	15-100%	54W